

Part No. HC0903E

Preview **PDF** Download HTML

HC0903E Datasheet (PDF) - JL World Company Limited.

Part No.	HC0903E
Description	Electro-Magnetic Sound Generators
File Size	470.45 Kbytes
Html View	1
Manufacturer	JLWORLD [JL World Company Limited.]
Direct Link	http://www.jlworld.com
Logo	

★ Value Applying Rated Voltage, Rated Frequency, 50% Duty Square Wave
 ⚙ Value Applying Rated Frequency, Sine Wave, Measuring Current 60μA

HC09E Series
 HC09F Series
 HC09G Series

Dimension
 Unit: mm
 Tolerance : 0.3mm

Frequency Response
 Applied Voltage : 1.5V, 50% Duty Square Wave
 Measuring Distance : 10cm

Specification (all data taken at 25°C unless otherwise specified)

Model	Rated Voltage (V)	Operating Voltage (V)	★Rated Current (mA)	Coil Resistance (Ω)	Coil Impedance (Ω)	★Sound Output at 10cm (dB)	Rated Frequency (Hz)	Operating Temperature (°C)	Storage Temperature (°C)	Housing Material	Weight (g)
HC0901E	1.5	1 - 2	≤80	5.5 ± 1	10	≥80	2731	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0903E	3	2 - 5	≤80	25 ± 4	40	≥82	2731	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0905E	5	4 - 7	≤80	40 ± 4	55	≥85	2731	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0901F	1.5	1 - 2	≤80	5.5 ± 1	10	≥80	3200	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0903F	3	2 - 5	≤80	25 ± 4	40	≥82	3200	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0905F	5	4 - 7	≤80	40 ± 4	55	≥85	3200	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0901G	1.5	1 - 2	≤80	5.5 ± 1	10	≥80	3100	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0903G	3	2 - 5	≤80	25 ± 4	40	≥82	3100	-20 ~ +60	-30 ~ +70	Noryl SE1	1
HC0905G	5	4 - 7	≤80	40 ± 4	55	≥85	3100	-20 ~ +60	-30 ~ +70	Noryl SE1	1

★ Value Applying Rated Voltage, Rated Frequency, 50% Duty Square wave
 ⚙ Value Applying Rated Frequency, Sine Wave, Measuring Current 60μA

www.jlworld.com

If the datasheet does not displayed, please, [download the Adobe Reader](#) or [click to view in HTML datasheet.](#)

Related Electronics Part Number

Part No.	Description	Html View	Manufacturer
STV83X7	TV sound processor with analog broadcast demodulator for A2 and NICAM standards	1 2 3 4	STMicroelectronics
95100	Comb Generators	1 2	Spectrum Microwave, Inc.
MSP34X1G	Multistandard Sound Processor Family with Virtual Dolby Surround	1 2 3 4 5 More	Micronas
MAX9471	Multiple-Output Clock Generators with Dual PLLs and OTP	1 2 3 4 5 More	Maxim Integrated Products
HC0901A	Electro-Magnetic Sound Generators	1	JL World Company Limited.
ISL14011	Low Jitter Clock Generators for Set-Top Box	1 2 3 4 5	Intersil Corporation
FMS6406_06	Precision S-Video Filter with Summed Composite Output Sound Trap and Group Delay Compensation	1 2 3 4 5 More	Fairchild Semiconductor
K3350K	IF Filter for Quasi/Split Sound Applications	1 2 3 4 5 More	EPCOS
AA8335	SOUND EFFECT PROCESSOR	1 2 3 4 5 More	Agamem Microelectronic Inc.

Link URL

<https://pdf1.alldatasheet.com/datasheet-pdf/view/291459/JLWORLD/HC0903E.html>Does ALLDATASHEET help your business so far? [[DONATE](#)]